


# AP-100AH/BR-100AH Firmware Update Procedure

This document describes how to update the firmware of AP-100AH/BR-100AH.

1. Start AMC Manager®, select the device you want to update the firmware from the device list and click the icon  from the toolbar. The firmware update window is displayed.
2. Click **Browse**, select **Firmware(\*.zip)** from the pull-down menu on the right of **File name** field and specify the downloaded firmware (APBR-100\_xxx.zip file).  
\* “xxx” of the file name “APBR-100\_xxx.zip” indicates the firmware version.
3. The file information of the selected firmware is displayed. Check the file information, check the check box at **Restart the device after the update** and click **Update Now**.
4. In the password entry screen, enter the password of the device and click **OK**. (This screen is not displayed when the password is not configured to the device.)
5. The firmware of the selected device has been updated.  
Click **Close** to close the **Firmware Update** window.

**NOTE:**

Do not turn off the AP-100AH/BR-100AH module while the firmware update is in progress.

6. In the main window of the AMC Manager®, check that the version information is changed for the device you have updated the firmware.

**Silex Technology America, Inc.**

URL: <https://www.silextechnology.com/>

Technical Support: [support@silexamerica.com](mailto:support@silexamerica.com)

Sales: [sales@silexamerica.com](mailto:sales@silexamerica.com)